

虛擬鍵的編碼 (Virtual-key Codes).....

常數名稱	十六進位值	十進位值	滑鼠或按鍵的對應值
VK_LBUTTON	01	1	滑鼠左鈕
VK_RBUTTON	02	2	滑鼠右鈕
VK_CANCEL	03	3	Control-break 執行
VK_MBUTTON	04	4	滑鼠中鈕
	05-07	5-7	未定義
VK_BACK	08	8	Backspace 鍵
VK_TAB	09	9	Tab 鍵
	0A-0B	10-11	未定義
VK_CLEAR	0C	12	Clear 鍵
VK_RETURN	0D	13	Enter 鍵
	0E-0F	14-15	未定義
VK_SHIFT	10	16	Shift 鍵
VK_CONTROL	11	17	Ctrl 鍵
VK_MENU	12	18	Alt 鍵
VK_PAUSE	13	19	Pause 鍵
VK_CAPITAL	14	20	Caps Lock 鍵
	15-19	21-25	保留給 Kanji 系統使用
	1A	26	未定義
VK_ESCAPE	1B	27	Esc 鍵
	1C-1F	28-31	保留給 Kanji 系統使用
VK_SPACE	20	32	SpaceBar 鍵
VK_PRIOR	21	33	Page Up 鍵
VK_NEXT	22	34	Page Down 鍵
VK_END	23	35	End 鍵
VK_HOME	24	36	Home 鍵
VK_LEFT	25	37	Left Arrow 鍵
VK_UP	26	38	Up Arrow 鍵
VK_RIGHT	27	39	Right Arrow 鍵
VK_DOWN	28	40	Down Arrow 鍵
VK_SELECT	29	41	Select 鍵
	2A	42	OEM 自訂使用

VK_EXECUTE	2B	43	Execute 鍵
VK_SNAPSHOT	2C	44	Print Screen 鍵
VK_INSERT	2D	45	Ins 鍵
VK_DELETE	2E	46	Del 鍵
VK_HELP	2F	47	Help 鍵
VK_0	30	48	0 鍵
VK_1	31	49	1 鍵
VK_2	32	50	2 鍵
VK_3	33	51	3 鍵
VK_4	34	52	4 鍵
VK_5	35	53	5 鍵
VK_6	36	54	6 鍵
VK_7	37	55	7 鍵
VK_8	38	56	8 鍵
VK_9	39	57	9 鍵
	3A-40	58-64	未定義
VK_A	41	65	A 鍵
VK_B	42	66	B 鍵
VK_C	43	67	C 鍵
VK_D	44	68	D 鍵
VK_E	45	69	E 鍵
VK_F	46	70	F 鍵
VK_G	47	71	G 鍵
VK_H	48	72	H 鍵
VK_I	49	73	I 鍵
VK_J	4A	74	J 鍵
VK_K	4B	75	K 鍵
VK_L	4C	76	L 鍵
VK_M	4D	77	M 鍵
VK_N	4E	78	N 鍵
VK_O	4F	79	O 鍵
VK_P	50	80	P 鍵
VK_Q	51	81	Q 鍵
VK_R	52	82	R 鍵

VK_S	53	83	S 鍵
VK_T	54	84	T 鍵
VK_U	55	85	U 鍵
VK_V	56	86	V 鍵
VK_W	57	87	W 鍵
VK_X	58	88	X 鍵
VK_Y	59	89	Y 鍵
VK_Z	5A	90	Z 鍵
	5B-5F	91-95	未定義
VK_NUMPAD0	60	96	數字鍵 0 鍵
VK_NUMPAD1	61	97	數字鍵 1 鍵
VK_NUMPAD2	62	98	數字鍵 2 鍵
VK_NUMPAD3	63	99	數字鍵 3 鍵
VK_NUMPAD4	64	100	數字鍵 4 鍵
VK_NUMPAD5	65	101	數字鍵 5 鍵
VK_NUMPAD6	66	102	數字鍵 6 鍵
VK_NUMPAD7	67	103	數字鍵 7 鍵
VK_NUMPAD8	68	104	數字鍵 8 鍵
VK_NUMPAD9	69	105	數字鍵 9 鍵
VK_MULTIPLY	6A	106	* 鍵
VK_ADD	6B	107	+ 鍵
VK_SEPARATOR	6C	108	Separator 鍵
VK_SUBTRACT	6D	109	- 鍵
VK_DECIMAL	6E	110	. 鍵
VK_DIVIDE	6F	111	/ 鍵
VK_F1	70	112	F1 鍵
VK_F2	71	113	F2 鍵
VK_F3	72	114	F3 鍵
VK_F4	73	115	F4 鍵
VK_F5	74	116	F5 鍵
VK_F6	75	117	F6 鍵
VK_F7	76	118	F7 鍵
VK_F8	77	119	F8 鍵
VK_F9	78	120	F9 鍵

VK_F10	79	121	F10 鍵
VK_F11	7A	122	F11 鍵
VK_F12	7B	123	F12 鍵
VK_F13	7C	124	F13 鍵
VK_F14	7D	125	F14 鍵
VK_F15	7E	126	F15 鍵
VK_F16	7F	127	F16 鍵
VK_F17	80	128	F17 鍵
VK_F18	81	129	F18 鍵
VK_F19	82	130	F19 鍵
VK_F20	83	131	F20 鍵
VK_F21	84	132	F21 鍵
VK_F22	85	133	F22 鍵
VK_F23	86	134	F23 鍵
VK_F24	87	135	F24 鍵
	88-8F	136-143	未指定
VK_NUMLOCK	90	144	Num Lock 鍵
VK_SCROLL	91	145	Scroll Lock 鍵
	92-B9	146-185	未指定
	BA-C0	186-192	OEM 自訂
	C1-DA	193-218	未指定
	DB-E4	219-228	OEM 自訂
	E5	229	未指定
	E6	230	OEM 自訂
	E7-E8	231-232	未指定
	E9-F5	233-245	OEM 自訂
	F6-FE	246-254	未指定

example :

```

procedure TForm1.DBEdit1KeyPress(Sender: TObject; var Key: Char);
begin
  if (Key = #13) // Enter 鍵
  then begin
    SendMessage(GetParentForm(Self).Handle, wm_NextDlgCtl, 0, 0);
    Key := #0;
  end
  else inherited KeyPress(Key);
end;

```

*CThing by 2001/01/25*